

X-Lyte 5 series motor specs

X-LYTE 5304 36V

R/MIN	N.M	WATT	AMPS	VOLTAGE
348	0.00	0.0000	1.2	36.0
338	3.06	0.1083	4.0	36.0
334	4.00	0.1399	5.0	36.0
330	4.98	0.1721	6.0	36.0
327	5.97	0.2044	7.0	36.0
323	6.96	0.2354	8.0	36.0
319	7.95	0.2656	9.0	36.0
315	8.99	0.2966	10.0	36.0
312	9.95	0.3251	11.0	36.0
308	11.03	0.3558	12.0	36.0
304	12.00	0.3820	13.0	36.0
301	13.00	0.4098	14.0	36.0
298	14.01	0.4372	15.0	36.0
294	15.01	0.4621	16.0	36.0
290	15.97	0.4850	17.0	36.0
283	16.89	0.5005	18.0	36.0

X-LYTE 5304 48V

R/MIN	N.M	WATT	AMPS	VOLTAGE
465	0.01	0.0005	1.2	48.0
454	2.80	0.1331	4.0	48.0
450	3.80	0.1791	5.0	48.0
446	4.79	0.2237	6.0	48.0
442	5.78	0.2675	7.0	48.0
438	6.78	0.3101	8.0	48.0
434	7.77	0.3531	9.0	48.0
431	8.76	0.3954	10.0	48.0
426	9.73	0.4341	11.0	48.0
422	10.79	0.4768	12.0	48.0
418	11.73	0.5135	13.0	48.0
414	12.60	0.5549	14.0	48.0
410	13.79	0.5921	15.0	48.0
406	14.80	0.6292	16.0	48.0
402	15.82	0.6660	17.0	48.0
398	16.80	0.7002	18.0	48.0
394	17.85	0.7365	19.0	48.0
390	18.81	0.7682	20.0	48.0

X-LYTE
5305 36V

R/MIN	N.M	WATT	AMPS	VOLTAGE
273	0.12	0.0034	1.2	36.0
260	4.28	0.1165	4.0	36.0
256	5.64	0.1612	5.0	36.0
252	6.77	0.1787	6.0	36.0
248	8.04	0.2088	7.0	36.0
244	9.39	0.2399	8.0	36.0
240	10.66	0.2679	9.0	36.0
236	11.96	0.2958	10.0	36.0
232	13.20	0.3207	11.0	36.0
227	14.55	0.3459	12.0	36.0
224	15.80	0.3706	13.0	36.0
221	17.02	0.3939	14.0	36.0
217	18.21	0.4138	15.0	36.0
212	19.62	0.4356	16.0	36.0
208	20.96	0.4565	17.0	36.0
205	22.10	0.4744	18.0	36.0
199	23.39	0.4874	19.0	36.0
196	24.55	0.5039	20.0	36.0

X-LYTE
5305 48V

R/MIN	N.M	WATT	AMPS	VOLTAGE
365	0.00	0.0000	1.2	48.0
352	4.16	0.1533	4.0	48.0
348	5.42	0.1975	5.0	48.0
344	6.72	0.2421	6.0	48.0
340	7.96	0.2834	7.0	48.0
336	9.26	0.3256	8.0	48.0
331	10.58	0.3667	9.0	48.0
327	11.81	0.4044	10.0	48.0
323	13.09	0.4428	11.0	48.0
320	14.36	0.4812	12.0	48.0
315	15.65	0.5162	13.0	48.0
311	16.39	0.5501	14.0	48.0
307	18.17	0.5841	15.0	48.0
303	19.50	0.6187	16.0	48.0
299	20.79	0.5510	17.0	48.0
295	22.01	0.6799	18.0	48.0
291	23.31	0.7103	19.0	48.0
287	24.57	0.7384	20.0	48.0